


The foot pedal FE-FS1-U1-U is equipped with a switching element, which contains one NC and one NO contact. It may e.g. be used for the selection of AKAS® Box bending function or opening of a press.

Switching diagram:

	free position	pressed down
23-24		
11-12		

Contact closed
 Contact open

Switching elements:



Execution	1-aluminum foot pedal heavy version free standing on slip elastic feet
Operating voltage	max. 500 VAC, 40-60Hz
Switching current	max. 10 A. For inductive and capacitive loads, a contact protection must be provided.
Operations	min. 10 Mio.
Contact Material	Silver
Connection type	Screwterminal
Electrical connection	0,5-1,5 mm ²
Cable entry	M20x1,5
Switching insert	1 changeover contact, positive opening
Switching function	Changeover
Switching system	Creep mechanism
Housing	Die cast aluminum, powder-coated RAL 7021 (dark gray)
Pedal	Die cast aluminum, powder-coated RAL 7021 (dark gray)
Accident cover	Die cast aluminum, powder-coated
Attachment	For mounting of the footpedal in the housing bottom (pedal area) are provided 2xØ4,5 and 2xØ6,5 holes (see drawing). Here threads can be cut. Alternatively, the rubber feet can be removed and these threads can be used as a mounting option.
Protection type	IP65 to IEC/EN 60529
Operating temperature	-30°C to +80°C
Regulations	IEC/EN 60947-5-1
Order code	FE-FS1-U1-U-xx (xx = RD = cover firered RAL 3000) (xx = YE = cover yellow RAL 1021)